# ACENERGY

www.acenergystore.com cs@acenergystore.com

**Power Station Experts** 

# **Acenergy Portable Power Station S2000**

2016Wh-- LiFePO4 (Lithium Iron Phosphate Battery)

## **Overview**

Acenergy Portable Power Station S2000 is designed to power your Laptop, Wi-Fi router, fibre router/ modem and to charge your mobile devices during power outages and load shedding.

#### **Features and Benefits**

With the latest technology built into a compactportable design. Capable of supplying power to many devices such as Laptops, Drone, Fibre router /modem, Desk lamps, TV, Decoders and to Built-in inverter provides:

- 4 x AC output to plug in your gadgets or appliances
- 2 x USB A Output
- 2 x USB C Output
- 1 x Car Charger
- 1 x AC Input
- 1 x Solar Panel Input

With the industry-leading technology, the S2000 can be charged within 2 hours via wall outlet. The Power Station has a built-in solar charge controller with a solar panel input which can be charged with a 500W solar panel.

## **Packaging Contents**

- 1 x Acenergy Portable Power Station
- 1 x Car Charge Cable
- 1 x AC Charger
- 1 x User Manual

#### **Dimensions and weight**

(LxW/xD):418\*280\*300MM/16\*11\*12IN

24.6kg= 54lb



# **Specification**

• Function: Portable Power Station

Capacity: 1008Wh

#### **PORTS**

- 4\*AC Output: 220V-50HZ, 110V-60HZ, Rated output 2000W
- 2\*USB A Output: Quick Charge 3.0, 18W Max
- 2\*USB C Output: PD100W
- 1\*Car Port Output: 12V,10A
- 1\*AC Input: 1200W
- 1\* Solar Charging Port: 500W

#### Certification:

FCC、UN38.3、UL2743、PSE、ETL、MSDS

#### Warranty:

a 3-year full-device warranty

