

# ACENERGY

www.acenergystore.com  
cs@acenergystore.com

Power Station Experts

## Acenergy Portable Power Station S1200 1008Wh-- LiFePO4 (Lithium Iron Phosphate Battery)

### Overview

Acenergy Portable Power Station S1200 is designed to power your Laptop, Wi-Fi router, fibre router/ modem and to charge your mobile devices during power outages and load shedding.

### Features and Benefits

With the latest technology built into a compact portable design. Capable of supplying power to many devices such as Laptops, Drone, Fibre router /modem, Desk lamps, TV, Decoders and to Built-in inverter provides:

- 2 x AC output to plug in your gadgets or appliances
- 3 x USB - A Output
- 3 x USB - C Output
- 1 x Car Charger
- 1 x AC Input
- 1 x DC Input
- 1 x Solar Panel Input

With the industry-leading technology, the S1200 can be charged within 1.5 hours via wall outlet. The Power Station has a built-in solar charge controller with a solar panel input which can be charged with a 500W solar panel.

### Packaging Contents

- 1 x Acenergy Portable Power Station
- 1 x Car Charge Cable
- 1 x AC Charger
- 1 x User Manual

### Dimensions and weight

(LxWxD):345\*220\*180MM/14\*9\*7.5IN

11.6kg= 26lb



### Specification

- Function: Portable Power Station
- Capacity: 1008Wh

### PORTS

- 2\*AC Output: 220V-50HZ, 110V-60HZ, Rated output 1200W
- 3\*USB-A Output: 2 \* 5V2.4A/1\*QC3.0, 0.9V2A
- 3\* USB-C Output: 2\*5V2.4A/1\*PD65W
- 1\*Car Port Output: 12V10A
- 1\*DC Input: 12V-30V
- 1\*AC Input:1000W
- 1\* Solar Panel Input: 500W

### Certification :

FCC, UN38.3, UL2743, PSE, MSDS, ETL

### Warranty:

a 3-year full-device warranty

